

## DS1000E, DS1000D Series Digital Oscilloscopes

DS1102E, DS1052E, DS1102D, DS1052D

### Product Overview

DS1000E, DS1000D series are kinds of economical digital oscilloscope with high-performance.

DS1000E series are designed with dual channels and 1 external trigger channel.

DS1000D series are designed with dual channels and 1 external trigger channel as well as 16 channels logic analyzer.



### Applications

- Electronic Circuit Test
- Circuit Functional Test
- Logical Relation Between Signals Verification
- Circuit of Mixed Signal Test
- Education & Training

### Easy to Use Design

- Built-in help menu enables information acquisition more convenient
- Multiple language menu and Chinese & English input
- Can store files in USB storage device or local the internal memory
- Analog waveform intensity can be adjusted
- To display a signal automatically by **AUTO**
- Pop-up menu makes it easy to read and use

### Main Features

- Dual analog channels and 16 channels logic analyzer, 100MHz maximum bandwidth, 1GSa/s maximum real-time sample rate and 25GSa/s maximum equivalent sample rate
- 5.6 inch 64k TFT LCD makes the waveform displays more clear and vivid
- Abundant trigger types: Edge, Pulse Width, Video, Slope, Alternate, Pattern and Duration
- Unique adjustable trigger sensitivity enables to meet different demands
- Enable to measure 22 types of wave parameters and track measurements via cursor automatically
- Unique waveform record and replay function
- Fine delayed scan function
- Built-in FFT function, hold practical digital filters
- Pass/Fail detection function enables to output testing results
- Multiple math operations for waveforms
- Powerful PC application software UltraScope
- Standard configuration interface: USB Device, USB Host, RS-232 and support USB storage device storage and PictBridge print standards
- The new function "Key Lock" can meet the needs of industrial production
- Support for remote command control

### F.E.S. Co., Ltd.

1000/24, P.B. Tower, 8 floor, Sukhumvit 71 Rd., North Klongtan, Wattana, Bangkok 10110

TEL: 02-064-4050 or 02-064-4051 | FAX: 02-010-4262 | Email: info@fesupply.com

www.fesupply.com | www.rigolthai.com


Line Official



Facebook



## ➤ Automatically Measure 22 Waveform Parameters




Automatic measure

DS1000E, DS1000D series oscilloscopes can measure 20 types of waveform parameters automatically, which contains 10 voltage and 12 time parameters.


In cursor mode, users can easily measure by moving cursor. 3 types of cursor measurement are optional: Manual, Track and Auto.

## ➤ Cursor Measure



FFT cursor measure

## ➤ Multiple Trigger



Pattern trigger

Both DS1000E and DS1000D series contain abundant triggers:


- Edge trigger, Pulse Width trigger, Video trigger, Slope trigger
- Alternate trigger, Pattern trigger (DS1000D), Duration trigger (DS1000D)

Especially the duration trigger is a new type from perfect combination of patten and pulse width trigger. Unique function of adjustable trigger sensitivity is good for filtering possible noise from signal in order to avoid false triggers.

## ➤ 16 Channels Logic Analyzer

Being equipped with 16 channels logic analyzer, DS1000D series mixed signal oscilloscopes achieve mixed signal measure coordinating with 2 analog channels.


Each channel can be turned on or off independently, or in groups of 8(D7-D0 and D15-D8); also, you can set waveform size and threshold types or change the display position on screen for digital channel.



Digital channels setup

## ➤ Waveform Recording


In virtue of waveform recording function from DS1000E and DS1000D, not only the outputs from two channels could be recorded, but also the waveforms outputted by Pass/Fail test could be easily recorded. Totally, up to 1000 frames of waveforms can be recorded. Besides, users can playback and save the waveforms to get better waveform analyzing result.




Waveform recording

## ➤ Pass/Fail Testing

The Pass/Fail function monitors the changes of signals by comparing whether the input signal is within the pre-defined mask. The testing results not only can be displayed on screen or output by isolated pass/fail port, but also can be alarmed according to turn on system sound.



Pass/Fail testing



Measurement window

## ➤ UltraScope Software

RIGOL provides powerful PC application software, UltraScope, which enables to capture and measure waveforms, to perform local or remote operation, to save waves as ".bmp" format, to save files as ".txt" or ".xls" format as well as to print waveforms.



Key Lock function

## ➤ Key Lock

This function is widely used in productions. All keys are locked except F1 to F5 and MENU ON/OFF in this mode.

To lock the keyboard, use menu; to unlock, correct password has to be input. Also, you can reset a new password if necessary.

## Specifications


All specifications apply to DS1000E, DS1000D Series Oscilloscopes unless otherwise noted. To come up to these specifications, two conditions must be met firstly:

- The instrument must have been operated continuously for 30 minutes under the specified operating temperature.
- Do perform Self-Calibration operation through the Utility menu if the range of operating temperature variations up to or more than 5°C.

**NOTE:** All specifications are guaranteed unless where marked "typical".

### Specifications

Bandwidth					
DS1102E		DS1052E		DS1102D	DS1052D
100MHz		50MHz		100MHz	50MHz
Acquisition					
Sample Modes		Real-Time Sample		Equivalent Sample	
Sample Rate		1GSa/s <sup>[1]</sup> , 500MSa/s		DS1102X	DS1052X
				25GSa/s	10GSa/s
Averages		The waveform will be displayed one time when all the channels finish N times sample. Wherein, N could be selectable from 2, 4, 8, 16, 32, 64, 128 and 256.			
Inputs					
Input Coupling		DC, AC, GND			
Input Impedance		1MΩ±2%, the input capacity is 18pF±3pF			
Probe Attenuation Factors		1X, 5X, 10X, 50X, 100X, 500X,1000X			
Maximum Input Voltage		400V (DC+AC Peak, 1MΩ input impedance)			
		40V (DC+AC Peak) <sup>[2]</sup>			
Time Delay between Channels (typical)		500ps			
Horizontal					
Sample Rate Range		Real-Time: 13.65Sa/s-1GSa/s Equivalent: 13.65Sa/s-25GSa/s			
Waveform Interpolation		Sin(x)/x			
Memory Depth		Channel Mode	Sample rate	Memory Depth (normal)	Memory Depth (long memory)
		Single channel	1GSa/s	16kpts	N.A.
		Single channel	500MSa/s or lower	16kpts	1Mpts
		Dual channel	500MSa/s or lower	8kpts	N.A.
		Dual channel	250MSa/s or lower	8kpts	512kpts
Scanning Speed Range (Sec/div)		2ns/div~50s/div, DS1102X 5ns/div~50s/div, DS1052X 1-2-5 Sequence			
Sample Rate and Delay Time Accuracy		±50ppm (any interval ≥1ms)			
Vertical					




A/D Converter	8-bit resolution, all channels sample simultaneously	
Volts/div Range	2mV/div~10V/div (at the input terminal connecting to BNC)	
Maximum Input	Maximum input voltage on analog channel CAT I 300Vrms, 1000Vpk; instantaneous overvoltage 1000Vpk CAT II 100Vrms, 1000Vpk RP2200 10:1: CAT II 300Vrms RP3300A 10:1: CAT II 300Vrms	
Offset Range	±40V (250mV/div~10V/div) ±2V (2mV/div~245mV/div)	
Analog Bandwidth	100MHz (DS1102D, DS1102E) 50MHz (DS1052D, DS1052E)	
Single-shot Bandwidth	100MHz (DS1102D, DS1102E) 50MHz (DS1052D, DS1052E)	
Selectable Analog Bandwidth Limit (typical)	20MHz	
Lower Frequency Response (AC, -3dB)	≤5Hz (at input BNC)	
Rise Time (typical at BNC, equivalent sample)	<3.5ns, <7ns, respectively at 100MHz, 50MHz	
DC Gain Accuracy	2mV/div-5mV/div: ±4% (In Normal or Average acquisition mode) 10mV/div-10V/div: ±3% (In Normal or Average acquisition mode)	
DC Measurement Accuracy (Average Acquisition Mode)	When vertical position is zero and N ≥16: ±(DC Gain Accuracy×reading+0.1div+1mV) When vertical position is not zero and N ≥16: ±[DC Gain Accuracy×(reading+vertical position)+(1% of vertical position) + 0.2div] When vertical scale is between 2mV/div and 245mV/div, add 2mV more for setting value. When vertical scale is between 250mV/div and 10V/div, add 50mV more for setting value.	
Delta Volts Measurement Accuracy (Average Acquisition Mode)	Under same setting and condition, the voltage difference (ΔV) between any two points in the waveforms coming from the average of more than 16 waves have been acquired: ±(DC Gain Accuracy×reading + 0.05 div)	
Trigger		
Trigger Sensitivity	0.1div~1.0div (adjustable)	
Trigger Level Range	Internal	±6 div from center of screen
	EXT	±1.2V
Trigger Level Accuracy (typical) applicable for the signal of rising and falling time ≥20ns	Internal	±(0.3div × V/div) (±4 divisions from center of screen)
	EXT	±(6% of setting + 200 mV)
Trigger Offset	In Normal mode: pre-trigger (memory depth/ 2*Sample rate), delayed trigger 1s	
	In Slow Scan mode: pre-trigger 6div, delayed trigger 6div	
Trigger Holdoff Range	500ns~1.5s	
Set Level to 50% (typical)	When input signal frequency ≥50Hz	
Edge Trigger		
Edge trigger slope	Rising, Falling, Rising + Falling	
Pulse WidthTrigger		
Trigger Condition	(>, <, =) Positive pulse width, (>, <, =) Negative pulse width	
Pulse Width Range	20ns ~10s	

<b>Video Trigger</b>		
Video Standard	Support for standard NTSC, PAL and SECAM broadcast systems. Line number range: 1~525 (NTSC) and 1~625 (PAL/SECAM)	
Line Frequency		
<b>Slope Trigger</b>		
Trigger Condition	(>, <, =) Positive slope, (>, <, =) Negative slope	
Time Setting	20ns~10s	
<b>Alternate Trigger</b>		
Trigger on CH1	Edge, Pulse Width, Video, Slope	
Trigger on CH2	Edge, Pulse Width, Video, Slope	
<b>Pattern Trigger</b> <sup>[2]</sup>		
Pattern Type	D0~D15 select H, L, X, $\frac{f}{2}$ , $\frac{f}{4}$	
<b>Duration Trigger</b> <sup>[2]</sup>		
Pattern Type	D0~D15 select H, L, X	
Qualifier	>, <, =	
Time Setting	20ns~10s	
<b>Measurements</b>		
Cursor	Manual	Voltage difference between cursors ( $\Delta V$ ) Time difference between cursors ( $\Delta T$ ) Reciprocal of $\Delta T$ in Hertz ( $1/\Delta T$ )
	Track	Voltage value and time value of waveform point
	Auto	Cursors are visible for Automatic Measurement
Auto Measure	Vpp, Vamp, Vmax, Vmin, Vtop, Vbase, Vavg, Vrms, Overshoot, Preshoot, Freq, Period, Rise Time, Fall Time, +Width, -Width, +Duty, -Duty, Delay1→2 $\frac{f}{2}$ , Delay1→2 $\frac{f}{4}$	
<b>Remarks:</b>		
[1] Only one channel is available when the Sample rate is 1GSa/s.		
[2] For DS1000D Series.		



## General Specifications

Display		
Display Type	145mm (5.6 inch) diagonal TFT Liquid Crystal Display	
Display Resolution	320 horizontal ×RGB×234 vertical pixels	
Display Color	64k color	
Display Contrast (typical)	150:1	
Backlight Brightness (typical)	300 nit	
Probe Compensator Output		
Output Voltage (typical)	Approximately 3Vpp (peak to peak value)	
Frequency (typical)	1kHz	
Power Supply		
Supply Voltage	100 ~ 240VAC <sub>RMS</sub> , 45~440Hz, CAT II	
Power Consumption	Less than 50W	
Fuse	2A, T level, 250 V	
Environmental		
Ambient Temperature	Operating 10℃~ 40℃	
	Non-operating -20℃~ +60℃	
Cooling Method	fan cooling	
Humidity	below +35℃: ≤90% relative humidity	
	+35℃~ +40℃: ≤60% relative humidity	
Altitude	Operating at 3,000 m or below	
	Non-operating at 15,000 m or below	
Mechanical		
Dimensions	Width	303mm
	Height	154mm
	Depth	133mm
Weight	Without package	2.3kg
	Packaged	3.5kg
IP Protection		
IP2X		
Calibration Interval		
The recommended calibration interval is one year		





## Ordering Information

### Name of Product

**RIGOL** DS1000E, DS1000D series oscilloscopes

### Standard Accessories

- Probex×2 (1.5m), (1:1 or 10:1 adjustable) Passive Probes
- A Power Cord that fits the standard of destination country
- A Data Cable (DS1000D series)
- An Active Logic Head (DS1000D series)
- 20 Logic Testing Nips (DS1000D series)
- 20 Logic Testing leads (DS1000D series)
- A Quick Guide

### Optional Accessories

- BNC Cable
- USB Data Cable
- RS232 Cable
- USB-GPIB Adapter
- DS1000E, DS1000D soft carrying case

## Warranty

Thank you for choosing **RIGOL** products!

**RIGOL** warrants that the product mainframe and product accessories will be free from defects in materials and workmanship within the warranty period.

If a product proves defective within the respective period, **RIGOL** guarantees free replacement or repair of any defective products within a reasonable period of time. To get repair service, please contact with your nearest **RIGOL** sales or service office.

There is no other warranty, expressed or implied, except such as is expressly set forth herein or other applicable warranty card. There is no implied warranty of merchantability or fitness for a particular purpose. Under no circumstances shall **RIGOL** be liable for any consequential, indirect, ensuing or special damages for any breach of warranty in any case.

## F.E.S. Co., Ltd.

1000/24, P.B. Tower, 8 floor, Sukhumvit 71 Rd., North Klongtan, Wattana, Bangkok 10110

TEL: 02-064-4050 or 02-064-4051 | FAX: 02-010-4262 | Email: info@fesupply.com

www.fesupply.com | www.rigolthai.com

